

FORMAT TO EDIT **ELTRON**

Label Format Name **ELTRON** Desc. **ELTRON LABEL**
 Number Across **1** Width **224** Starting Ending FF **N**

*1 = Item Code	?S2?D6?M17??0?B	<=====	SETUP LINE
*2 = Description	?A11 COMPANY NAME?,	<=====	TEXT LINE
*3 = Price	?A13?{*1}?,	<=====	BARCODE LINE
*4 = Sale Price	?A11 *2?,	<=====	TEXT LINE
*5 = Unit of Measure	?A11 \$*3 *5?,	<=====	TEXT LINE
*6 = Category	?E?p001?,	<=====	END LINE
*7 = Class	DONE	<=====	END OF FORMAT
*8 = Price Level #2			
*9 = List Price			
*10= Manuf. Code			
*11= Field 1			
*12= Field 2			
*13= Field 3			
*14= Serial #			
*15= Location			

Type **DONE** to end

===== SETUP LINES EXPLAINED

?S2 = PRINTER SPEED
 ?D6 = PRINT DARKNESS
 ?M17 = # OF DOTS FROM LEFT OF PRINTER (only used with smaller labels)
 ??0 = BARCODE TYPE (0= CODE128 FULL ASCII)
 ?B = BEGIN BUFFER MODE

===== TEXT LINES EXPLAINED

?A11 = PRINT FOLLOWING IN SINGLE WIDTH , SINGLE HEIGHT
 *1 = VARIABLE TO PRINT (SEE LIST)
 ?, = CARRIAGE RETURN

===== BARCODE LINES EXPLAINED

?A13 = PRINT THE FOLLOWING IN SINGLE WIDTH, TRIPLE HEIGHT
 {*1} = BARCODE TO PRINT WITH HUMAN READABLE CHARACTERS BELOW
 ?, = CARRIAGE RETURN

===== END LINE EXPLAINED

?E = END BUFFER MODE
 ?p001 = PRINT 1 LABEL
 ?, = CARRIAGE RETURN

Tel (954)772-8995
 Fax(954)772-9806